

# MediaStar DVB-S/S2 LAN-Caster Gateway for Digital Satellite Re-Broadcast over IP (784)



## Key Features for

- Supports both SD & HDTV transmissions (DVB-S/S2)
- PCMCIA CI CAM Slot for multiple channel decryption
- Auto configuration with MediaStar Media Manager Software
- Compact, Up to 9 Units in 3RU
- Delivers up to 15 channels of TV and Radio from a DVB-S multiplex
- IP command pass through and IR Routing support
- Easy software upgrade path; non CAM to CAM operation
- Low power consumption (7W)

The MediaStar range of DVB-S LAN-Caster Gateways are a powerful and ultra reliable, solid state "out of the box" solution for satellite TV reception and when used in conjunction with the MediaStar DVB-T LAN-Casters and MPEG Encoders, will meet your entire IP Television Headend, Digital Signage and Digital Media encoding and distribution requirements.

The MediaStar Evolution LAN-Caster streams live Digital Satellite TV and Radio channels such as news, sport and entertainment directly onto your IP network.

The unit is a 'hot swappable' blade that easily fits into a MediaStar Powered Chassis (Part 770) which has a capacity for up to nine units.

When connected to a DVB-S/S2 dish antenna signal the LAN-Caster can stream up to 15 channels of TV and Radio from an RF multiplex to any networked PC using the MediaStar Media Portal (Part 470) or video screens equipped with MediaStar Digital Media Decoder (Part 780).

Where the incoming transmissions are encrypted, a PCMCIA slot located securely within the rear of the unit allows for the insertion of a CI CAM module with its subscription card.

Initial configuration and stream setup using a laptop or tablet can be via the built in web server with its advanced web UI or by simply using the front panel buttons and LCD status display.

Alternatively, multiple units within a system can be networked under the control of the MediaStar Media Manager software (Part 462).

Front panel RS232 and USB Comms connectors allow local connectivity and can also be utilised to pass IP command signals generated by remotely located Touch Screens and management systems, for control of headend located RS232 devices.

Twin Infra red blasters enable IR commands from III party RCUs to be passed back from any display screen equipped with a MediaStar Media Decoder (Part 780) to the 784 for the control of other headend located IR devices.

Software upgrade options enable very cost effective initial system implementation with future proofed CAM capability available when needed using a software enablement code and with no hardware change.

This coupled with maintenance free operation, small physical size and low power consumption make the 784 ideally suited for both large scale distributed applications or simple single unit deployments. Please see model options below.

**Model options:** 784-S2, 784-S2-CI

# Specifications

## System Input

### RF Input

RF input of Digital Satellite Television (DVB-S2) TV and radio channels via a 75ohm type F female connector

### RF Frequency range:

950 to 2150 MHz

### RF Input level:

-65 to -25 dBm

### RF loop-through:

F type female connector (75 Ohms), unity gain (+/-5 dB), for connecting additional MediaStar DVB-S2 LAN-Caster units to multiplexes on the same polarity and frequency band.

### LNB voltage:

13/18 V, 22 KHz signalling, Maximum current drain 400 mA (short circuit protected)

Maximum 770 Rack LNB current 2,350 mA

DiSEqC v1.0, 1.1

## Cam Support

### CAM Support:

CI CAM modules supported with all common decryption standards (Irdeto, Viaccess, Conax, Nagravision etc.)

Single and professional multi-channel CAMs supported (processing 2, 8 & 12 simultaneously encrypted channels)

PCMCIA connector, 5V and 3V CAMs supported

## Network & Interfaces

### LAN:

RJ45 802.3 10/100 Base-T Auto MDIX

Static or DHCP IP Address

DSCP stream tagging for QoS

### Network Protocols:

UDP, TCP, ARP, DHCP, ICMP, IGMP V2, HTTP, Telnet, SNMP, Syslog, SAP/SDP, SMTP, DSCP

### USB Comms:

USB 1.1 Serial Comms for external configuration and or control

### RS232 Port:

Rx, Tx, CTS, RTS up to 11,5200 Baud Configured for SIPI external configuration/control OR IP to RS232 bidirectional pass through for external device control

### Infra-Red Blasters:

2 separate outputs supporting Sky, Sky+, SkyHD IR formats with web page or IP command remote activation.

Remote IP command generates any IR remote control keypress

30 - 56 KHz modulated IR waveforms supported

#### Vertrieb / Distributor:

**VIDELCO** Europe GmbH – Professionelle Audio-, Video-, Medien-Technik

Fon: +49 (0)2102 / 86 39-00 • Fax: +49 (0)2102 / 86 39-17 • [info@videlco.eu](mailto:info@videlco.eu) • [www.videlco.eu](http://www.videlco.eu)

## Configuration & Monitoring

### Unit configuration:

Via On board web server using laptop or tablet

Via front panel buttons and LCD status display

Remotely using MediaStar Media Manager software

### Control Interface:

RS232, USB 1.1 serial interface

Telnet for third part connectivity via TCP control such as touch panel interfaces

### External IP control interface:

ASCII Command/configuration via IP interface

USB comms and RS232 comms interfaces

### Upgradability:

Enablement code to upgrade from non CAM to CAM support (in situ, with no hardware change required)

### Software:

Fully upgradable ONLY with protected Cabletime software from an HTTP server

### SAP Announcements:

SAP (Session Announcement Protocol) notification of IP streams

### Temperature Monitoring:

Unit operating temperature available remotely via web interface

### Event Monitoring:

Key operating functions reported via SNMP or Syslog traps sent to third party SNMP manager (MIB available on request)

Automatic e-mail of Event log files via external SMTP server

## Other Information

### Power:

7 W (from 770 rack, excluding external LNB load)

### Weight:

405 g

### Dimensions:

129 x 41 x 225 mm, occupies 1 (of 9) 770 rack slot

### Environmental:

0° - 40°C, 32 - 104 °F (770 rack ambient)

### Approvals:

FCC, CE, CB, TUV Approved

### What's in the box?

784 DVB Lan-Caster Unit; Quick Start Guide; RJ45 Patch Cable 2.0m;

#### Vertrieb / Distributor:

**VIDELCO** Europe GmbH – Professionelle Audio-, Video-, Medien-Technik

Fon: +49 (0)2102 / 86 39-00 • Fax: +49 (0)2102 / 86 39-17 • [info@videlco.eu](mailto:info@videlco.eu) • [www.videlco.eu](http://www.videlco.eu)